fade midi fixed
origin natural tuneable

installation





How to Install

- Cut hole in ceiling as per above cut-out; attach first fix plaster plate.
- Wire luminaire cable to Orluna certified driver, ensuring correct polarity (brown to red LED output 1 [+], white to black LED output 1 [-], red to red LED output 2 [+], black to black LED output 2 [-])
- With mains supply switched off, connect driver to mains supply (to avoid damaging the luminaire, do not hot-wire);
- Press the luminaire into plaster frame, ensuring Ø250mm around luminaire and driver is left clear of insulation.

Luminaire Details

Cut-out	Ø64mm	Class	III
Recess Depth	96mm	IP Rating	IP54/IP65
Clearance	Ø250mm	IP Zone	Zone 1
Fixing Method	Plaster-in/Garter spring	Material	Aluminium ADC12
Min Ceiling Thickness	N/A	Cable type	4 Core 0.75mm²
Max Ceiling Thickness	28mm	Cable Length	300mm
Max Driver Distance	20m	Bezel Temp	F Rated

ORLUNA LED Technologies Limited,
Unit A, Chiltern Park Industrial Estate,
Dunstable,
Bedfordshire LU5 4LT
United Kingdom

info@orluna.com

+44 (0) 1923 889 712

orluna